٠

Step 1: Download and Install vCastSender on your phone from Play Store.



Step 2: Make sure the phone and Projector is connected to the same network.

Step 3:Open vCastSender and select Device list icon on the left bottom of the screen

vCastSender

Please Enter PIN Code connect to ViewBoard





SM-S9180 🖉

Step 4: Open Settings Network Settings on the projector to find the IP address.



Step 5: Find the projectors IP address in vCastSender's device list and click on it.

VCastSender									
đ	Device List								
52\$\$\$new		172.21.10.187							
Cast-6124		172.21.12.62							
ViewSonic PJ-5512	2	172.21.9.216							
Cast-4233		172.21.10.31							
NOMVDIC 1142		172.21.10.29							
ViewSonic PJ-6634	4	172.21.10.120							
NOMVDIC 3226		172.21.10.150							
Cast-4155		172.21.10.143							
Cast-5421		172.21.10.169							
Cast-2001		172.21.13.73							
Cast-2455		172.21.9.110							
SM-S9180 🖉	172.21.8.170	VSaccess							

Step 6: Once connected successfully, you will see the below.



Step 7: Click on the display icon on the left side.

×	ViewSonic	**				÷	1:4	7 PM	$\ >$
			হু Wi	Fi					ŝ
					<	Enable	>		Ś
			SSI	D		VSaccess			-
			Cor	nfigure IP	<	Automatic	>		
			IP A	Address					
	Network Settings	Sut	onet Mask	255.255.248.0					
			Def	ault Gateway	172.21.8.1				(1.8)
			DN	S Server		172.21.1.27		, Fr	
									\bigcirc
									Ŵ
									Ó

Step 8: Now your phone is mirrored to the projector. Please find the below video for your reference.

How to use VCastSender